

55750SE

OPTICAL SYSTEM AND A TARGET-SEEKING SYSTEM
5 COMPRISING AN OPTICAL SYSTEM

BACKGROUND OF THE INVENTION AND PRIOR ART

10 The present invention concerns an optical system comprising a first optical unit and a first sensor unit for sensing electromagnetic radiation. The optical system is arranged such that incident electromagnetic radiation that originates from some scene outside of the optical system can reach the first sensor unit by passing via the first optical unit and by following a beam path from the first optical unit
15 to the first sensor unit.

WO 97/05742-A1 describes such a system. The system can be used for detecting infra-red (IR) radiation. The system can for example be used in a target-seeking missile. The document describes
20 a switchable mirror which can be set in two different positions. In a first position, the mirror is not active. In this position, radiation from an observed scene which goes in through an objective lens can reach a detector array. In a second position of the mirror, radiation from said scene is prevented from reaching the detector array. Instead,
25 radiation from a light emitting diode is reflected towards the detector array. The light emitting diode is used as a temperature reference. In this system, it takes a relatively long time to move the mirror from the first to the second position and vice versa.

30 SUMMARY OF THE INVENTION

The inventor of the present invention has found that it would be desirable to be able to quickly switch the electromagnetic radiation which is present between the first optical unit and the first sensor unit in a system of the kind which has been described in the first
35 paragraph above. Such a quick switching can be advantageous for many different reasons. Among other things, such a quick switching

can be used for reducing the probability that the optical system is discovered by devices which search for retroreflexes from such an optical system. Furthermore, such a quick switching can be advantageous in order to prevent that the system is destroyed by destroying radiation. Different other advantages of the system according to the invention will be clear from the description below.

The above mentioned purpose and advantages are achieved according to the invention with an optical system of the kind which is described in the first paragraph above and which is characterised in that the optical system also comprises a micromirror matrix unit which comprises a large number of micromirror elements and which is arranged in said beam path, wherein the micromirror matrix unit is arranged to be able to be set in at least a first and a second state, wherein in said first state the micromirror matrix unit reflects said incident electromagnetic radiation which reaches the micromirror matrix unit from the first optical unit such that this electromagnetic radiation reaches the first sensor unit, wherein in said second state the micromirror matrix unit reflects said incident electromagnetic radiation which reaches the micromirror matrix unit from the first optical unit such that this electromagnetic radiation does not reach the first sensor unit.

By positioning such a micromirror matrix unit in the beam path, the radiation can be switched very quickly. A micromirror matrix may for example be made to switch between two states in less than 10 μ s. The micromirror matrix may thus very quickly be switched between said first and second states. This has many advantages in different contexts. If the optical system for example is used as a target-seeking system, the optical system may be exposed to retroreflex searching. Electromagnetic radiation which enters through the first optical unit and which is led to the first sensor unit can be reflected back the same way, since the first sensor unit usually is positioned such that possible reflections from the sensor unit at least partly are reflected back in the opposite direction to the incident radiation. This is used in so-called retroreflex searching. Such a search is done in such a manner that the searching device scans over a cer-

tain area in order to look of retroreflexes. In such a manner, the optical system can be discovered. Through the present invention, the radiation can however be switched very quickly. It is therefore not necessary that radiation from the first optical unit is led to the first sensor unit the whole time. Further advantages of the invention will be described below.

It can be noted that it is known to in a different manner use a micromirror matrix unit in an IR-detecting system. US 5,323,002 thus describes that a light modulator may consist of a digital micromirror device (DMD). This light modulator is used in the beam path from a reference source to a detector. The radiation which has been reflected by the light modulator passes through a none-imaging optics and further to the detector via a "chopper".

According to an advantageous embodiment of the present invention, the first sensor unit comprises a large number of sensor elements and is arranged to be positioned in an image plane in the optical system, which image plane is arranged to be able to constitute an image plane for said scene. The first sensor unit is thus usually arranged in an image plane for the scene in question. There are different kinds of sensor systems, inter alia so-called staring systems and scanning systems. In a scanning system, the electromagnetic beam is scanned in one or two directions. If the radiation is scanned in two directions, the sensor unit needs only consist of a single sensor element. However, it is advantageous if the sensor unit comprises a large number of sensor elements. The sensor elements may be arranged in a row. In this case, the beam in question is suitably scanned in one direction (crosswise to the row) such that the row of sensor elements can sense the whole scene from which the electromagnetic radiation originates. By using a plurality of sensor elements, the scene may thus be sensed faster.

According to a further advantageous embodiment, the first sensor unit is such that said sensor elements are arranged as a two-dimensional array of sensor elements and wherein the optical system is constructed as a staring system. Since the sensor elements

are arranged as a two-dimensional array, no means are needed in order to scan the beam in question. The system is thus in this case "staring". This is advantageous, since the scene thereby can be sensed quickly since all sensor elements at the same time can sense different parts of the scene. Furthermore, the system can be made smaller and more simple, since no scanning element is needed.

The image plan, in which the first sensor unit is positioned, is suitable arranged in the optical system such that it constitutes an image plane for said scene when said scene is positioned at such a large distance from the optical system that rays from a point in said scene reach the first optical unit as at least substantially parallel rays. The optical system is particularly suited to be used when the scene is positioned at a relatively large distance from the optical system. The electromagnetic radiation from the scene can thereby be considered to consist of completely or at least substantially parallel rays which enter into the first optical unit.

Preferably, the first sensor unit is arranged to sense radiation within the infra-red wavelength range. The system is particularly suited to be used for detecting IR-radiation.

The optical system can also comprise a second sensor unit for sensing electromagnetic radiation arranged such that when the micromirror matrix unit is set in a state which is different from said first state, the micromirror matrix unit reflects said incident radiation which reaches the micromirror matrix unit from the first optical unit such that this electromagnetic radiation reaches the second sensor unit. Suitably, the micromirror matrix unit can be set in said second state when it is set such that the incident electromagnetic radiation reaches the second sensor unit. The second sensor unit can thereby be of another kind than the first sensor unit such that the second sensor unit is less disposed to be destroyed by electromagnetic radiation than the first sensor unit. The second sensor unit can for example be used if the optical system is exposed to destroying radiation. A switching can then take place such that the

second sensor unit is used instead of the first sensor unit. The second sensor unit can thereby be used for, for example, directing a counter attack against the source of the destroying radiation.

- 5 For example, the second sensor unit can be a quadrant detector. The second sensor unit is suitably not arranged in an image plane for said scene. A quadrant detector is relatively durable and inexpensive to produce. Such a detector is therefore suitable to be used for the second sensor unit. If it is desired to sense an electromagnetic beam from some destroying source, no image needs to be
10 formed on this sensor unit. Consequently, the second sensor unit is suitable not arranged in an image plane.

- The optical system can be arranged to prevent the incident electromagnetic radiation from said scene from being reflected back to this
15 scene from the second sensor unit. This can be done in different manners. For example, an optical isolator can be arranged in the beam path between the first optical unit and the second sensor unit. The second sensor unit can thereby be arranged somewhat inclined, such that it is not arranged perpendicularly relative to the
20 incident radiation. This reduces the risk for retroreflexes.

- The optical system may suitably comprise at least one reference source for emitting electromagnetic radiation of a known kind, wherein this reference source is arranged such that electromagnetic
25 radiation from the reference source reaches the first sensor unit when the micromirror matrix unit is set in a state which differs from said first state. Such a reference source can be used for calibrating the sensor unit. For an IR-system, the reference source thus constitutes a temperature reference. Preferably, the reference source
30 can be set at two different temperatures in order to improve the calibration of the sensor unit.

- According to an advantageous embodiment, the reference source is
35 arranged such that electromagnetic radiation from the reference source reaches the first sensor unit when the micromirror matrix unit is set in said second state. The calibration of the first sensor

unit can thereby take place as soon as the micromirror matrix unit is set in said second state.

5 The optical system suitably comprises a control unit which controls at least the setting of said micromirror matrix unit. The control unit can also control the sensing of the first sensor unit, such that the first sensor unit is sensed at a plurality of occasions per second, wherein the control unit is arranged to between these two sensing occasions control the micromirror matrix unit such that it is not in
10 said first state. The first sensor unit thereby only needs to be engaged to sense said scene during the short times when it is actually sensed with regard to incident radiation. Between these occasions, the first sensor unit is disengaged from the incident radiation from said scene. This means that the risk that the optical system is dis-
15 covered by a device which performs retroreflex searching is reduced.

According to an advantageous embodiment, the optical system comprises means for detecting if the optical system is exposed to
20 scanning or destroying radiation, wherein the control unit is arranged to control the micromirror matrix unit such that said first state is avoided when said means has detected such a radiation.

Suitably, the micromirror matrix unit is thereby controlled such that
25 it reflects said incident electromagnetic radiation such that it reaches the second sensor unit. Said means for detecting if the optical system is exposed to scanning or destroying radiation can consist of the first sensor unit together with the control unit. The control unit can thus register if suspected scanning radiation is inci-
30 dent onto the first sensor unit. Alternatively, a separate detector can be used for detecting such radiation. As soon as such radiation is detected, the micromirror matrix unit is suitably switched. Such a switching of the micromirror matrix unit can take place very quickly. Thereby the first sensor unit is protected from being exposed to de-
35 stroying radiation. The second sensor unit can, as has been explained above, be designed to be less sensitive of destroying radiation.

The control unit can also be arranged to individually control the setting of the mirror elements of the micromirror matrix unit in such a manner that the amount of electromagnetic radiation which is reflected by the micromirror matrix unit towards the first sensor unit is controlled by the setting of the mirror elements of the micromirror matrix unit. The micromirror matrix unit can thereby be used for so-called dynamic control. By for example "angling away" a number of mirror elements which are randomly selected, the electromagnetic radiation which is reflected towards the first sensor unit is reduced. It can also be possible to control the setting of the mirror elements such that for example certain peripheral mirror elements are "angled away". If the micromirror matrix unit is suitably positioned in the beam path, the micromirror matrix unit can thereby function in a similar manner as a traditional aperture in a camera system.

The invention also concerns a target-seeking system. This target-seeking system comprises according to the invention an optical system according to any of the preceding embodiments. The target-seeking system is for example a target-seeking missile. The invention is particularly useful in connection with such target-seeking systems.

SHORT DESCRIPTION OF THE DRAWINGS

The present invention will now be explained with the help of embodiments, given as examples, and with reference to the annexed drawings.

Fig. 1 shows schematically an optical system according to the invention with the micromirror matrix unit set in a first state.

Fig. 2 shows schematically the optical system according to fig. 1 but with the micromirror matrix unit set in a second state.

Fig. 3 shows schematically a target-seeking missile.

DESCRIPTION OF EMBODIMENTS OF THE INVENTION

5

Fig. 1 shows schematically an optical system according to the invention. The optical system comprises a first optical unit 10. Fig. 1 also schematically illustrates a scene in the form of an aeroplane 12 which is located outside of the optical system. The scene 12 is usually located at a large distance from the optical system such that incident electromagnetic radiation 14 from the scene 12 is incident on the first optical unit 10 as parallel rays.

The optical system also comprises a micromirror matrix unit 16 and a first sensor unit 18 for sensing electromagnetic radiation. The micromirror matrix unit 16 has a large number of micromirror elements. Such a micromirror matrix unit (DMD) 16 can for example be of the kind which is provided by Texas Instruments Incorporated in Dallas, Texas. A DMD can for example consist of 1280 x 1024 micromirror elements. Each micromirror element may for example be about the size 16 μm x 16 μm .

The micromirror matrix unit 16 is able to be set in at least a first and a second state. In the first state, for example all micromirror elements can be arranged in one of their end positions. If a sufficient flatness can be achieved, it is also conceivable that all micromirror elements are in their neutral rest position when the micromirror matrix unit 16 is set in the first state. In the second state of the micromirror matrix unit 16, the micromirror elements are suitably arranged such that they are set in their second end positions. In fig. 1, the micromirror matrix unit 16 is considered to be set in the first state. In this state, the micromirror matrix unit 16 reflects the electromagnetic radiation from the first optical unit 10 such that this radiation reaches the first sensor unit 18. The micromirror matrix unit 16 is thus arranged in the beam path 20 from the first optical unit 10 to the first sensor unit 18.

The first sensor unit 18 is according to this embodiment of the kind where a large number of sensor elements are arranged as a two dimensional array. An example of such a sensor unit is the sensor unit BD MM 003 which is delivered by Sofradir in Chatenay-
5 Malabry, France. Such a sensor unit may for example have 128 x 128 sensor elements. The first sensor unit 18 is thus suitably arranged in an image plane, where an image of the scene 12 is formed. According to the schematic set up which is shown in fig. 1, this means that the first sensor unit 18 is positioned in the focal
10 plane of the first optical unit 10. It should however be noted that fig. 1 only shows a schematic embodiment. There may in fact be more optical units along the beam path 20. For example, an optical unit may also be arranged in the beam path 20 between the micromirror matrix unit 16 and the first sensor unit 18.

15 It should also be noted that the embodiment according to fig. 1 is a so-called "staring system". Alternatively, it is also possible to use a scanning system. In such a system, no two-dimensional sensor unit of the kind which is shown in fig. 1 is needed. Instead one or two
20 scanning elements are arranged in the beam path 20.

The first sensor unit 18 is preferably arranged to sense IR radiation. In order to be able to calibrate the first sensor unit 18, the optical system also comprises a reference source 22. The reference source
25 22 emits electromagnetic radiation 24 of a known kind, i.e. the reference source 20 constitutes a temperature reference. Preferably, also this temperature can be varied such that the reference source 22 can emit radiation representing at least two different temperatures. When the micromirror matrix unit 16 is set in the first state,
30 radiation 24 from the reference source 22 does not reach the first sensor unit 18. The radiation 24 from the reference source 22 is here represented by broken lines.

According to the preferred embodiment, the optical system comprises also a second sensor unit 26. The second sensor unit is
35 suitably of a more simple and more inexpensive kind than the first sensor unit 18. The second sensor unit 26 may for example consist

of a quadrant detector. Such a sensor unit 26 is less sensitive and less disposed to be destroyed by electromagnetic radiation than the first sensor unit 18. In fig. 1 also an optical isolator 30, which will be described more closely in connection with fig. 2, is schematically shown.

The optical system also comprises a control unit 32. The control unit 32 controls the optical system and co-ordinates the different units with each other. It is thus shown in fig. 1 that the control unit 32 is connected to the micromirror matrix unit 16, the first sensor unit 18, the second sensor unit 26 and the reference source 22.

As has been mentioned above, there is a risk that the optical system is exposed to searching radiation. With the help of such searching radiation, an area is searched in order to discover retro-reflexes. When such searching radiation enters through the first optical unit 10, this radiation can be reflected by the first sensor unit 18 and exit through the first optical unit 10 to be detected by the searching device. In order to reduce the probability that such a retroreflex via the first sensor unit 18 arises, the control unit 32 is suitably arranged to control the micromirror matrix unit 16 such that the incident radiation from the scene 12 only intermittently reaches the first sensor unit 18. The optical system usually works with a certain image frequency. For example, the image frequency can be 50 Hz, i.e. the first sensor unit 18 is sensed 50 times per second. However, each sensing occasion only needs to last a few ms, for example, less than 5 ms. The control unit 32 can thus control the micromirror matrix unit 16 such that the micromirror matrix 16 assumes said first state only during the time when the first sensor unit 18 is sensed. Therefore, the larger part of the time, no retroreflex via the first sensor unit 18 can occur. This reduces the risk for discovery by the such searching radiation.

The optical system can also be arranged with means for detecting such searching radiation. This can be done in that the control unit 32 registers that the first sensor unit 18 is exposed to such radiation. The control unit 32 can thereby be arranged to immediately

switch the micromirror matrix unit 16 such that it is no longer in said first state. The micromirror matrix unit 16 can thus be set in at least a second state.

5 Fig. 2 shows schematically the same system as fig. 1 but with the micromirror matrix unit 16 set in a second state. In this second state, the micromirror matrix unit 16 is set such that incident radiation 14 from the scene 12 does not reach the first sensor unit 18 but instead is directed towards the second sensor unit 26. Since the
10 second sensor unit 26 according to this example is a quadrant detector, the second sensor unit 26 is suitably not positioned exactly in an image plane.

If the first sensor unit 18 has been exposed to searching radiation,
15 the micromirror matrix 16 is thus switched such that the radiation is directed in the manner that is shown in fig. 2. After the discovery with the help of searching radiation, usually a destroying radiation follows from the device which previously emitted the searching radiation. The purpose of such destroying radiation is to destroy the
20 optical system, in particular the first sensor unit 18. Since the micromirror matrix unit 16 is set in the state which is shown in fig. 2, such a destruction of the first sensor unit 18 is however avoided. Instead, the destroying radiation is directed towards the second sensor unit 26. This second sensor unit 26 is, as mentioned above,
25 less disposed to be destroyed by such destroying radiation. At the same time, the second sensor unit 26 can be used for controlling a counter attack against the device which emits the destroying radiation. It is thereby advantageous if the optical system does not reflect the destroying or searching radiation back. This can according
30 to the invention be achieved in different manners which can also be combined. The second sensor unit 26 can be arranged such that it is not arranged perpendicularly to the incident radiation. This reduces the risk for retroreflex. Furthermore, as has been mentioned, the second sensor unit 26 is preferably not arranged in an image
35 plane. The destroying radiation which hits the second sensor unit 26 is thereby more scattered, which reduces the amount of retroreflected radiation. Furthermore, an optical isolator 30 can be ar-

ranged in the beam path towards the second sensor unit 26. Such an optical isolator 30 can be constructed in different manners which are known to a person skilled in the art. For example, such an optical isolator may consist of a linear polariser in series with a so-called $\lambda/4$ plate. When the device which emits the destroying radiation has been destroyed, or when destroying or scanning radiation is no longer detected, the control unit 32 can control the micromirror matrix unit 16 such that it returns to the first state which is shown in fig. 1.

The reference source 22 is suitably arranged such that when the micromirror matrix unit 16 is in the second state as shown in fig. 2, radiation from the reference source 22 is directed towards the first sensor unit 18. The first sensor unit 18 can thus be calibrated when the micromirror matrix 16 is in the second state. When the optical system works normally (i.e. when it is not exposed to searching or destroying radiation), the system works, as mentioned above, suitably with a certain image frequency. As has been mentioned above, the micromirror matrix unit 16 is suitably switched to the second state between each sensing. Between these sensings, when the micromirror matrix 16 is in the second state, radiation from the reference source 22 can thus be directed towards the first sensor unit 18. A calibration of the first sensor unit 18 can thus take place between the sensings with the normal image frequency. If possibly a longer time is needed for the calibration, some image may be left out in the normal image frequency. Of course, suitable optics can be arranged in the beam path 24 between the reference source 22 and the first sensor unit 18. Such optics may suitably be arranged in the beam path 24 between the reference source 22 and the micromirror matrix unit 16. Such an optic can consist of a non-imaging optic, for example of the kind which is shown in the above mentioned US 5,323,002.

The control unit 32 can also be arranged to individually control the setting of the micromirror elements of the micromirror matrix unit 16 such that the amount of electromagnetic radiation which is reflected by the micromirror matrix unit 16 towards the first sensor unit 18

can be controlled by the setting of the mirror elements. In this manner, the micromirror matrix unit 16 may be used to control the intensity of the radiation that is incident onto the first sensor unit 18. The intensity can be varied by turning away randomly selected mirror elements of the micromirror matrix unit 16. If the micromirror matrix unit 16 is positioned in a suitable position the beam path 20, also selected mirror elements, for example in the periphery of the micromirror matrix 16, be turned away such that the micromirror matrix unit 16 functions in a similar manner as a normal camera aperture.

In the embodiment above, it is specified that the micromirror matrix unit 16 can be set in a first and a second state. With a more advanced micromirror matrix unit 16 it is conceivable that the micromirror matrix unit 16 can assume more than two states. It is thus conceivable that in a first state, incident radiation is directed towards the first sensor unit 18, in a second state, incident radiation is directed towards the second sensor unit 26 and in a third state, incident radiation is neither directed towards the first sensor unit 18 nor towards the second sensor unit 26.

The optical system may suitable be used in a target-seeking system. Such a target-seeking system can for example be arranged on the ground or in an aeroplane. According to a possible embodiment according to the invention, the target-seeking system is a target-seeking missile 34 (see fig. 3) in which an optical system according to the invention is arranged.

As is clear from the description above, the invention has several advantages. Since the micromirror matrix unit 16 quickly can be switched between at least a first and a second state, the risk that the optical system is discovered by a system that works with retro-reflex searching is reduced. Even if such searching radiation is detected, the risk that the optical system is destroyed is reduced since the micromirror matrix unit 16 quickly can be switched to a second state. In this second state, the optical system may also be used to control a counter attack against the device which emits destroying

radiation, since the second sensor unit 26 can be engaged for this purpose when the micromirror matrix unit 16 has assumed the second state. Furthermore, according to the invention so-called dynamic control is achieved since individual mirror elements in the micromirror matrix unit 16 can be directed such that the amount of radiation which reaches the first sensor unit 18 (and also the second sensor unit 26) can be controlled. Furthermore, the possibility to quickly make calibrations with the help of the reference source 22 is improved. This makes it possible to correct so-called pattern noise in an efficient manner with the help of the invention.

The present invention is not limited to the described embodiments. The invention may thus be modified and varied within the scope of the following claims.

15

20